

NX100 AM Transmitter

making digital broadcasting work

PHONE +1.902.823.2233 FAX +1.902.823.3183

183 info@nautel.com

www.nautel.com

G E N E R A L

Transmitter Type Medium wave, AM, 100% solid state

Configuration

Forty RF power modules, each including a single integrated RF amplifier/modulator

No frequency dependant parts in RF module

Each module is hot pluggable and has internal microcontroller for protection and monitoring over a serial bus

Short circuit protection at the module level offers an added layer of protection

Dual redundant digital single board exciters utilizing FPGA/DSP technology with automatic changeover

Pre-correction utilized specifically to improve digital performance

Redundant low voltage power supplies

RF Output Power Maximum: 150 kW RMS

Peak Power: 552 kW

Carrier Power Range: 0 to 110 kW

Up to 62 preset levels, presets may include other operational parameters such as DRM vs Analog and different program inputs Output level stabilized against AC supply voltage variations Built in Dynamic Carrier Control

Built in AM stereo

RF Output Connection 3 1/8 EIA female standard, other outputs on request RF Output Impedance

50 ohms, unbalanced

Efficiency 90% typical at 100 kW

RF Load VSWR

16,000 peak reflected watts (1.5:1 VSWR @ 100 kW, 100% modulation) results in instantaneous power shutback

4000 reflected watts RMS (1.5:1 VSWR @ 100 kW, 0% modulation) results in a graceful power reduction

Frequency Range 531 kHz to 1,620 kHz. "Quick frequency change capability"

Frequency Stability ±2 ppm over temperature range

Optional 300 ppb ovenized source with GPS option

Modulation Type 6 phase direct digital modulation

1.8 MHz modulation sample rate

Modulation Capability 135% positive peak modulation to 100 kW 120% positive peak modulation to 110 kW

Spurious and Harmonic

Meets ITU-R SM.328-10 Meets ITU-R SM.329-9

AC INPUT

Voltage 340 V to 440 V, 3 phase or to customer specifications

Power Supply Variation ±10% voltage, 47 Hz to 63 Hz

Power Consumption

111 kW typical at 100 kW, 0% modulation 167 kW typical at 100 kW, 100% modulation

Cos (theta)

0.95 typical

ENVIRONMENTAL

Temperature Range 0°C to + 50°C Derate 3°C per 500 m above sea level (2°C per 1,000 ft)

Humidity Range 0% to 95% non-condensing

Altitude 0 m to 4,000 m (0 ft to 13,000 ft)

Cooling Air Requirements 2,550 m³/hr (1,500 CFM)

SAFETY

Meets EN60215: 1976 Safety Requirements for Radio Transmitting Equipment





NX100 AM Transmitter

making digital broadcasting work

PHONE +1.902.823.2233 FAX +1.902.823.3183

info@nautel.com www.nautel.com

PHYSICAL

Dimensions

Transmitter Cabinet 184 cm H x 95.7 cm W x 120 cm D (72.4" H x 37.7" W x 47.2" D)

External Transformer Cabinet 116.8 cm H x 113 cm W x61 cm D (46" H x 44.5" W x 24" D)

Weight

Main transmitter cabinet with modules installed: 567 kg (1250 lbs)

Power transformer: 753 kg (1659 lbs)

A U D I O P E R F O R M A N C E

Analog Broadcast Inputs

Dual AES-EBU Digital Audio inputs* adjustable from -30dBFS to 0dBFS for 100% modulation

600 ohms balanced analog audio input +10 dBm nominal for 100% modulation, adjustable from -10 to +12 dBm

Digital Broadcasting Inputs

I,Q over AES-EBU, SRC available* with sample rate converter

I,Q over LVDS, 3 pairs, Clock, Data, frame sync *Two AES-EBU inputs provided and may be used for either analog audio or digital I,Q inputs

Optional Embedded DRM Generator/Content Server

Optional Embedded HD Radio Generator (Exgine™)

Frequency Response +0.2 dB/-0.8 dB, 30 Hz to 10,000 Hz.

Optional audio input filters available to meet regional bandwidth restrictions

Total Harmonic Distortion

Better than 0.8% (THD), 30 Hz to 10,000 Hz at 95% modulation (typical)

Intermodulation Distortion

SMPTE 1:1 Ratio, 60Hz/7kHz, 95% Mod Peak -0.5% @ 100kW (typical) DIM-B, 2.96kHz/9kHz, 80% Mod Peak - 0.5% @ 100kW

Carrier Shift

0.5% or less

Hum and Noise

-65 dB or better below 100kW, 100% modulation

CONTROL AND MONITORING

Extensive Control/Monitoring/Troubleshooting system through 17" front panel LCD touchscreen. Touch panel control system is non-critical and may be removed from the system without affecting transmitter operation or remote control/monitor via direct wired connections. Redundant back-up control interface provides control in case of front panel computer system failure. Built in instrumentation providing detailed spectrum/impedance and modulation analysis.

Metering

Cube DC Voltages (B+, PA and 15V) DC Current Sample Levels (PDM and RF Drive) Fan Speeds Heat Sink Temperature

Rack

DC Voltage levels (15V, 5V, 30V, 48V and B+) Rectifier Fan Speeds DC Current Rectifier Heat Sink Temperature AC Voltage

Exciter

Output Current (RMS, Peak, Carrier) Output Voltage (RMS, Peak, Carrier) Forward Power (RMS, Peak, Carrier) Reflected Power (RMS, Peak, Carrier) Audio/Modulation Levels (RMS and Peak - Positive/Negative) Load Impedance Controller PDM and RF Drive Levels Ambient Temp

RF Monitor

RF monitor is a power sample (using a directional coupler) that will allow for accurate audio performance measurements

Status

Easy access to current transmitter operating state, past and present alarm conditions and historical trends of both digital and analog channels

Schedule

Intuitive easy to read built in scheduler

Up to 144 yearly rules can be defined by user

Remote Control/ Monitoring

Three Remote interfaces:

- Direct wired optically isolated inputs and open collector outputs
- Web interface All locally available control is available over TCP/IP web interface
- SNMPv1

COMPLIANCE

Product complies with:

- ISED specification BETS-5 issue 1
- FCC CFR title 47 part 2 and part 73
- Conforms with all essential requirements of Radio European Directive 2014/53/EU

Notes:

Specifications defined in a laboratory environment with high grade source and demodulation equipment. Standard factory measurements does not include all items.



